

FiberBasix 100 TESTERS

EOT-100 Optical Loss Test Set ELS-100 Light Source EPM-100 Power Meter

NETWORK TESTING—OPTICAL



- Cost-effective, rugged handheld instruments designed for reliable performance
- Easy-to-use interface for error-free testing
- Interchangeable connectors, for first-class flexibility
- Particularly suited to the testing and troubleshooting of fiber-optic networks located within the premises

Introducing EXFO's FiberBasix testers, a series of handheld instruments designed to meet your basic day-to-day test requirements while helping you stay within budget. These worry-free, straightforward solutions provide the tools you need to accurately measure signal attenuation during fiber-optic cable installation.

The FiberBasix 100 series includes three highly convenient instruments:

- The **EOT-100 Optical Loss Test Set**, a versatile instrument that combines a power meter and a light source
- The **ELS-100 Light Source**, combining up to four wavelengths and available in four specific configurations
- The **EPM-100 Power Meter**, which offers high accuracy and referencing capabilities

FTTx Ready

EXFO's FiberBasix testers allow for the testing of passive optical networks (PONs) at 1310 nm, 1490 nm and 1550 nm, the three wavelengths recommended by the ITU-T (G.983.3) for PONs.



ELS-100 Light Source: Multiwavelength Capability

EXFO's ELS-100 Light Source provides excellent stability and high measurement accuracy for up to three singlemode wavelengths or two multimode wavelengths. It is the perfect complement to the FiberBasix EPM-100 Power Meter when it comes to measuring attenuation on fiber-optic links.



The ELS-100 Light Source

EOT-100 OLTS: Integrating a Power Meter and a Multiwavelength Light Source

The EOT-100 Optical Loss Test Set delivers power meter functionalities and your choice of up to three wavelengths from the following: 850 nm, 1300 nm, 1310 nm, 1490 nm or 1550 nm. Thanks to the EOT-100's highly flexible design, you can simultaneously measure the attenuation on two fiber links using two units.



The EOT-100 OLTS

EPM-100 Power Meter: High Accuracy and Easy Referencing

The EPM-100 Power Meter provides highly accurate power measurements, as well as reference value setting capabilities. What's more, this convenient unit requires no offset nulling, and it offers power autonomy of 300 hours, for reliable, long-lasting performance in the field.



The EPM-100 Power Meter

ELS-100 SPECIFICATIONS^a

Model ^b	23BL	235BL	12D	01-VCL
Central wavelength (nm)	1310 ± 20	1310 ± 20	850 ± 25	850 ± 20
	1550 ± 20	1490 ± 10	1300 +50/-10	
	1550 ± 20			
Spectral width ^c (nm)	≤ 5	≤ 5	50/135	≤ 1
Output power (dBm)	≥ 1/≥ 1	≥ 1/≥ -4.5/≥ -3	≥ -20/≥ -20 (62.5/125 μm)	≥ -3 (50/125 μm)
Power stability ^d (dB)				
	8 hours ± 0.10	± 0.10	± 0.10	± 0.25
Battery life (hours) (typical)	50	45	55	250
Warranty and recommended calibration interval (years)	1	1	1	1

EOT-100 SPECIFICATIONS^a

Model ^e	EOT-102	EOT-102X
Power meter port	Ge	GeX
Power range (dBm) ^f	10 to -60	26 to -50
Range displayed (dBm)	Down to -65	Down to -50
Number of calibrated wavelengths ^g	6	6
Power uncertainty ^h	± 5 % ± 1 nW	± 5 % ± 10 nW
Resolution (dB)	0.01 ⁱ	0.01 ^j
Automatic offset nulling ^k	Yes	Yes
Warmup time (s) ^{k, l}	0	0
Display units	dB/dBm/W	dB/dBm/W
Screen refresh rate (Hz)	3	3
Battery life (hours) (typical)	260	260
Warranty and recommended calibration interval (years)	1	1

Model ^b	23BL	235BL	12D	01-VCL
Central wavelength (nm)	1310 ± 20	1310 ± 20	850 ± 25	850 ± 20
		1550 ± 20	1490 ± 10	1300 +50/-10
			1550 ± 20	
Spectral width (nm) ^c	≤ 5	≤ 5	50/135	≤ 1
Output power (dBm)	≥ 1/≥ 1	≥ 1/≥ -4.5/≥ -3	≥ -20/≥ -20 (62.5/125 μm)	≥ -3 (50/125 μm)
Power stability (dB) ^d				
	8 hours ± 0.10	± 0.10	± 0.10	± 0.25
Battery life (hours) (typical)	50	45	55	250
Warranty and recommended calibration interval (years)	1	1	1	1

EPM-100 SPECIFICATIONS^a

Model ^e	EPM-102	EPM-102X
Power meter port	Ge	GeX
Power range ^f (dBm)	10 to -60	26 to -50
Range displayed (dBm)	Down to -65	Down to -50
Number of calibrated wavelengths ^g	6	6
Power uncertainty ^h	± 5 % ± 1 nW	± 5 % ± 10 nW
Resolution (dB)	0.01 ⁱ	0.01 ^j
Automatic offset nulling ^k	Yes	Yes
Warmup time ^l (s)	0	0
Display units	dB/dBm/W	dB/dBm/W
Screen refresh rate (Hz)	3	3
Battery life (hours) (typical)	> 300	> 300
Warranty and recommended calibration interval (years)	1	1

GENERAL SPECIFICATIONS

Size (H x W x D)	18.5 cm x 10.0 cm x 5.5 cm	(7 1/4 in x 4 in x 2 1/8 in)
Weight	0.4 kg	(0.9 lb)
Temperature		
	operating -10 °C to 50 °C	(14 °F to 122 °F)
	storage -40 °C to 70 °C	(-40 °F to 158 °F)
Relative humidity	0 % to 95 % non-condensing	

STANDARD ACCESSORIES

User guide, Certificate of Calibration, instrument stickers in four languages, AC adapter, connector adapter (FOA-XX), three AA batteries, wrist strap, alcohol cleaning pads.

SAFETY

21 CFR 1040.10 and IEC 60825-1:1993+A1:1997+A2:2001:
CLASS 1M LASER PRODUCT

Notes

- Guaranteed unless otherwise specified.
- All specifications valid at 23 °C ± 1 °C, with an FC connector.
- rms for lasers and FWHM for LEDs; typical values for LEDs.
- After 15 minutes warmup; expressed as ± half the difference between the maximum and minimum values measured during the period, with an APC connector on the power meter.
- All specifications valid at 1550 nm and 23 °C ± 1 °C, with an FC connector.
- In CW mode; sensitivity defined as 6 x rms noise level.
- Wavelengths: 850 nm, 1300 nm, 1310 nm, 1490 nm, 1550 nm and 1625 nm.
- Traceable to NIST; EOT-102X: up to 20 dBm.
- From 10 dBm to -50 dBm.
- From 26 dBm to -35 dBm.
- Power > -40 dBm for EOT-102, and > -25 dBm for EOT-102X.
- For ± 0.05 dB, from 18 °C to 28 °C.

ORDERING INFORMATION

ELS-100-XX-XX

Model

- ELS-100-12D = 850/1300 nm LED (62.5/125 mm)
- ELS-100-23BL = 1310/1550 nm laser (9/125 mm)
- ELS-100-235BL = 1310/1490/1550 nm laser (9/125 mm)
- ELS-100-12D-23BL = 850/1300 nm LED (62.5/125 mm), 1310/1550 nm laser (9/125 mm)
- ELS-100-01-VCL = 850 nm VCSEL (50/125 mm)

Connector*

- 50 = FC/PC ^a
- 54 = SC/PC ^a
- 74 = ST/PC ^a
- 89 = FC/UPC ^b
- 90 = ST/UPC ^b
- 91 = SC/UPC ^b
- EI-EUI-89 = UPC/FC narrow key ^c
- EI-EUI-90 = UPC/ST ^c
- EI-EUI-91 = UPC/SC ^c
- EI-EUI-95 = UPC/E-2000 ^c

Notes

- a. Multimode only
- b. Singlemode only
- c. Interchangeable connection

Example: ELS-100-12D-23BL-EI-EUI-89

EOT-10X-XX-XX

Model

- EOT-102-12D = Ge detector, 850/1300 nm LED (62.5/125 mm)
- EOT-102-23BL = Ge detector, 1310/1550 nm laser (9/125 mm)
- EOT-102-235BL = Ge detector, 1310/1490/1550 nm laser (9/125 mm)
- EOT-102X-23BL = High-power Ge detector, 1310/1550 nm laser (9/125 mm)
- EOT-102X-235BL = High-power Ge detector, 1310/1490/1550 nm laser (9/125 mm)
- EOT-102-01-VCL = Ge detector, 850 nm VCSEL (50/125 mm)

Connector Adapter (Power Meter)*

- FOA-22 = FC (PC/SPC/UPC/APC), NEC-D3
- FOA-32 = ST (PC/SPC/UPC)
- FOA-54 = SC (PC/SPC/UPC/APC)
- FOA-96B = E-2000
- FOA-98 = LC

Connector (Source)*

- 50 = FC/PC ^a
- 54 = SC/PC ^a
- 74 = ST/PC ^a
- 89 = FC/UPC ^b
- 90 = ST/UPC ^b
- 91 = SC/UPC ^b
- EI-EUI-89 = UPC/FC narrow key ^c
- EI-EUI-90 = UPC/ST ^c
- EI-EUI-91 = UPC/SC ^c
- EI-EUI-95 = UPC/E-2000 ^c

Notes

- a. Multimode only
- b. Singlemode only
- c. Interchangeable connection

Example: EOT-102X-235BL-FOA-22-EI-EUI-89

EPM-10X-XX

Model

- EPM-102 = Ge detector
- EPM-102X = High-power Ge detector

Connector Adapter*

- FOA-22 = FC (PC/SPC/UPC/APC), NEC-D3
- FOA-32 = ST (PC/SPC/UPC)
- FOA-54 = SC
- FOA-96B = E-2000
- FOA-98 = LC

Example: EPM-102X-FOA-22

TEST KIT ORDERING INFORMATION

FBK-101-XX LAN Test Kit

- EPM-102-XX Power Meter, Ge detector
- ELS-100-12D-XX Light Source, 850/1300 nm LED (1 port)
- One TJ-DXX-XX Test Jumper
- Carrying case GP-10-061

FBK-102-XX Outside Plant Test Kit

- EPM-102-XX Power Meter, Ge detector
- ELS-100-23BL-XX Light Source, 1310/1550 nm laser (1 port)
- One TJ-BXX-XX Test Jumper
- Carrying case GP-10-061

FBK-103-XX Contractor Test Kit

- EPM-102-XX Power Meter, Ge detector
- ELS-100-12D-23BL-XX Light Source, 850/1300 nm LED and 1310/1550 nm laser (2 ports)
- One TJ-BXX-XX Test Jumper
- One TJ-DXX-XX Test Jumper
- Carrying case GP-10-061

FBK-104-XX GigE Test Kit

- EPM-102-XX Power Meter, Ge detector
- ELS-100-01-VCL-XX Light Source, 850 nm VCSEL (1 port)
- One TJ-CXX-XX Test Jumper
- Carrying case GP-10-061

FBK-105-XX CATV Test Kit

- EPM-102X-XX Power Meter, high-power Ge detector
- ELS-100-23BL-XX Light Source, 1310/1550 nm laser (1 port)
- One TJ-BXX-XX Test Jumper
- Carrying case GP-10-061

FBK-106-XX Bidirectional MM Premise Test Kit

- Two EOT-102-12D-XX OLTs, Power Meter with Ge detector, 850/1300 nm LED source
- Two TJ-DXX-XX Test Jumpers
- Carrying case GP-10-061

* Other connectors and connector adapters available.

Consult our website at www.EXFO.com/accessories for details.

Find out more about EXFO's extensive line of high-performance portable instruments by visiting our website at www.EXFO.com.

EXFO Corporate Headquarters > 400 Godin Avenue, Quebec City (Quebec) G1M 2K2 CANADA | Tel.: 1 418 683-0211 | Fax: 1 418 683-2170 | info@EXFO.com

Toll-free: 1 800 663-3936 (USA and Canada) | www.EXFO.com

EXFO Montreal	2650 Marie-Curie	St-Laurent (Quebec) H4S 2C3 CANADA	Tel.: 1 514 856-2222	Fax: 1 514 856-2232
EXFO Toronto	160 Drumlin Circle	Concord (Ontario) L4K 3E5 CANADA	Tel.: 1 905 738-3741	Fax: 1 905 738-3712
EXFO America	3701 Plano Parkway, Suite 160	Plano, TX 75075 USA	Tel.: 1 800 663-3936	Fax: 1 972 836-0164
EXFO Europe	SOUTHAMPTON > Omega Enterprise Park, Electron Way	Chandlers Ford, Hampshire S053 4SE ENGLAND	Tel.: +44 2380 246810	Fax: +44 2380 246801
EXFO Asia	151 Chin Swee Road, #03-29 Manhattan House	SINGAPORE 169876	Tel.: +65 6333 8241	Fax: +65 6333 8242
EXFO China	No.88 Fuhua, First Road Central Tower, Room 801, Futian District	Shenzhen 518048, CHINA	Tel.: +86 (755) 8203 2300	Fax: +86 (755) 8203 2306
	Beijing New Century Hotel Office Tower, Room 1754-1755 No. 6 Southern Capital Gym Road	Beijing 100044 P. R. CHINA	Tel.: +86 (10) 6849 2738	Fax: +86 (10) 6849 2662

EXFO is certified ISO 9001 and attests to the quality of these products. This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation. EXFO has made every effort to ensure that the information contained in this specification sheet is accurate. All of EXFO's manufactured products are compliant with the European Union's WEEE directive. For more information, please visit www.EXFO.com/recycle. However, we accept no responsibility for any errors or omissions, and we reserve the right to modify design, characteristics and products at any time without obligation. Units of measurement in this document conform to SI standards and practices. Contact EXFO for prices and availability or to obtain the phone number of your local EXFO distributor.

For the most recent version of this spec sheet, please go to the EXFO website at <http://www.EXFO.com/specs>

In case of discrepancy the Web version takes precedence over any printed literature.